## **Table of Contents**

Installing Zebra Printer	2
Installing Custom Label	6

## **Installing Zebra Printer**

Your Zebra printer came with the installation CD. Plug in the CD and when the installation program starts, select Windows Drivers.



On the next screen, select Zebra EPL on the left and ZEBRA TLP2824 on the right. Click the Next button.

Printer Driver Setup Wizard	×
Printer Select Click the manufacturer and model of you	ır printer
Manufacturers:	Printers:
ZEBRA CPCL ZEBRA EPL ZEBRA ZPL	Zebra       LP2443         Zebra       LP2722         Zebra       LP2742         Zebra       LP2824         Zebra       LP2684         Zebra       LP2824         Zebra       TLP2722         Zebra       TLP2742         Zebra       TLP2742         Zebra       TLP3742         Zebra       2746
	< Back Next > Cancel

After the printer installation is finished, find the printer in the Windows Control Panel and right-click it. Select Properties from the popup menu.

rintin	g 🛛 👼 Set as	default	<u>84. (</u>	Select printing	nreferences	»	
	Name	Docur		Open			,
	PD	F reDirec	۲	Run as admin	istrator	•	
	Rev	ady		Set as Default	Printer		
	Qu	ickBook		Printing Prefe	erences		
	Rei	ady		Pause Printin	9		
×	Sar	msung S		Sharing			
Ê	Rei	ady		Use Printer Of	ffline		
		esigner \$		Refresh			
	🤝 Re	ady		Create Shorto	ut		
=	ZD	esigner 1		Delete			
	Rei	ady		Rename			
	Zel 0	bra LP28		Properties			
	🤝 Re	ady	_				
		hra TLP29	R74				

on or an	Charing	Porte	Advanced	Color Mana	aamaat	Coourity	Printer	About	1	
	Shanny	TOILS	Auvanceu		gement	Security	THILE	About		
17										
S)	Ze	bra LP28	324							
Locatior	n:									
~	. –									
Lommer	nt:									
Model:	Zeb	ora LP28	24							
Model: Featur	Zeb res	ora LP28	24							
Model: Featur Color:	Zeb res No	ora LP28	24 Pap	per available:						
Model: Featur Color: Doubl	Zeb res No e-sided: N	vra LP28 No	24 Pap Us	per available: er Defined						
Featur Color: Doubl Staple	Zeb No e-sided: No e: No	vra LP28	24 Pap Us 1.( 1 (	per available: er Defined 00" x 1.00" - ( 00" x 3.00" - (	2.54cm x	2.54cm				
Model: Featur Color: Doubl Staple Speed	Zeb No e-sided: N e: No d: Unknov	vra LP28. No	24 Pap Us 1.0 1.1	per available: er Defined 00" x 1.00" - ( 00" x 3.00" - ( 12" x 1.25" - (	2.54cm x 2.54cm x 2.86cm x	2.54cm 7.62cm 3.18cm				
Model: Featur Color: Doubl Staple Speed Maxim	Zeb No No e-sided: No e: No d: Unknov num resolu	vn vn vn: 203	24 Pap 1.0 1.0 1.1 0 dpi 1.1	per available: er Defined 00" x 1.00" - ( 00" x 3.00" - ( 12" x 1.25" - ( 12" x 4.00" - (	2.54cm x 2.54cm x 2.86cm x 2.86cm x	2.54cm 7.62cm 3.18cm 10.16c	-			
Model: Featur Color: Doubl Staple Speed Maxim	Zeb No le-sided: N e: No d: Unknov num resolu	vn vn ution: 203	24 Pap Us 1.0 1.1 1.1 1.1	per available: er Defined 00" x 1.00" - ( 00" x 3.00" - ( 12" x 1.25" - ( 12" x 4.00" - (	2.54cm x 2.54cm x 2.86cm x 2.86cm x	2.54cm 7.62cm 3.18cm 10.16c				
Model: Featur Color: Doubl Staple Speec Maxim	Zeb No le-sided: No e: No d: Unknov num resolu	vn nition: 203	24 Pap Us 1.0 1.1 1.1 Printing Prefe	per available: er Defined 00" x 1.00" - ( 00" x 3.00" - ( 12" x 1.25" - ( 12" x 4.00" - (	2.54cm x 2.54cm x 2.86cm x 2.86cm x	2.54cm 7.62cm 3.18cm 10.16c				

On the printer Properties screen, click Printing Preferences.

On the next screen, select an appropriate label size.

E Zebra LP2824 Printing Preferences	x
Document Options	
Zebra LP2824	
🖥 💱 Paper/Output	
Paper Layout: Portrait	
Rotate 180: Off	
🖶 🖶 📸 Media Settings	
🖬 🕀 🎼 Document Options	
🖬 🖶 🌠 Device Options	
🗄  🎲 User Commands	
Wizard Configuration Assistant	
OK Cancel Apply	

Click OK to finish the printer configuration procedure.

## **Installing Custom Label**

Open your company in Almyta and go to the System menu tab, Add-in Manager. Click the Add New button. Browse to the label. In this document ,we have browsed to the ALMS125A.accde file. This label is located on the Almyta original CD, AddIns folder. Select the file and click Open or just double-click the file name.



You should see the selected label in the list of installed optional modulus.



Exit the screen. Restart Almyta Control System and go to the System menu tab, Default Documents and Screens. Select the label in the Available Documents dropdown field for the Inventory Labels. Exit the screen.

	Home	Orders	Inven	tory As	sets	Reports	System	Data	Report Prev	view A
Options	Default D and S	ocuments creens	Add-In Manager	Customize Reports	💽 Ur 💾 Cu 街 Re	nhide Fields Istomize All start	S Comp Comp Logo Barco	oany Location s * ode Formats	ns 🔹 🔩 Err 曕 File * 🛛 🖧 Sha	or Log es in Use ared Comp
	(	Configurat	ion		A	Actions			I	nformation
🔳 Defa	ault Docur	ments & S	creens							
Docum	nent Type			Avail	able Doo	cuments			Printer	
Bill Of Lading (Manifest) === not select									Default	
Custo	m Label	s		Stan	Standard				Default	
Inven	tory Lab	els		Labe	l 2-25 x	1-25 (125A	)	•	Zebra Tl	P2824

Go to the Inventory menu tab, and select Locate and Move. We assume you have received some inventory units by this time. Click the View button. On the next screen, mark a couple of units, and click the Labels button.

9	Home	C	Orders	Inv	ventory	Assets	Re	eports	System	Data	Rep	oort Previe	w Add	-Ins	Hel
Direct Receive	Receive by Seria	Lo I and	Cate Move	Quick Move	Direct Issue	Reconcile ties	Lease	Warranty Repairs	Find Shipp or Consum	ped It ned Ma	em aster	Q Search I ☐ Active It ☐ Bill Of M	item Master iems ≠ Materials List	: : : :	Alterna Wareh Repair
E L Rec	ocate Inv	entor	y ate:						Report ar	nd Cycle	Counts	Section	3	c	
Rec	ceiving F oplied B	: == rh	Selecte ne Loca	d Items ation	; Lot	/Serial Nu	mber	Serial Nu	mber 2	Ne	ŧt	Received	– Warr/E	Exp.	⊟ X Mar
<u>Iter</u> <u>Cat</u>	<u>m ID:</u> tegory:	►/	LB PO	RT	13: 684	1345 4646				4. 48.	0 05/ 0 05/	16/2008 16/2008			
Loc Cer	<u>ation:</u>		LB PO LB PO	RT	79	7979				48. 480.	0 05/ 0 05/	16/2008 16/2008			
Lea	ised to C	ĺ	<u>L</u> abe	ls					🗢 Issu	ie <u>S</u>	plit Lot	. <u>M</u> o	ve 🚺		3
Lot, Lot	/Serial I	Rec umbe	ord: 14	4 26	of 87		K No	Filter Se	arch	•	_			1	
			/iew		Cl <u>e</u> ar Al		🕈 Exit				[	•			

On the next screen, choose "One Label per Row" and click the Preview button.

Adjust Number	Ut Units	_
Item ID	Item Description	Number Of Labels
A PALLET1	Mushrooms 10 cans per case	1
A PALLET1	Mushrooms 10 cans per case	1
	Copies Each:   1   2   3  One Label Per Row	4

In the Report Preview menu tab, click Page Setup.

Home Orders Inventory Assets Rep	ports System	Data Report Pre	eview Add-In	is Help 🕜
Print Quick Export to PDF MS Word MS Excel Output	Image: Show N       Image: Show	Aargins ata Only Is Page Setup	Zoom	Close Print Preview Close Previ
Item ID: A_PALLET1 DATE 05/16/2008	B Item ID: /	A_PALLET1	DATE 0	95/16/2008

On the Page Setup screen, Page tab, make sure the proper label size is selected.

Page Setup
Print Options Page Columns Orientation Orientation Paper Size: 2.25" x 1.25" - (5.71cm x 3.18cm) Source: Documents
Source <ul> <li>Printer for Label 2-25 x</li> <li>Default Printer</li> <li>Use Specific Printer</li> <li>Printer</li> </ul>
OK Cancel

Switch to the Print Options tab, and set margins: 0.01, 0.01, 0.1, 0.01 or as shown on the snapshot. Click OK to permanently save the changes.

Page Setup Print Option Margins (i	s Page Columns	Sample
Top: Bottom: Left: Right:	0.007 0.007 0.1 0.007	Characterized Internet I can be a set of the set I can be a set of the set I can be a set of the set I can be a set of the set of the set I can be a set of the set of the set I can be a set of the set of the set I can be a set of the set of the set I can be a set of the set of the set I can be a set of the set of the set I can be a set of the set of the set I can be a set of the set of the set of the set I can be a set of the set of the set of the set I can be a set of the se
Print Da Split Form Print F Print D	ta Only form Only Patasheet Only	
	ОК	Cancel

Print the labels by clicking Print or Quick Print button.



Close the Label Preview when finished.



The inventory labels can be printed anytime from the Selected Units screen as shown above or from the Receiving screens as shown below.

	Home	Orders	Inve	ntory	Asset	s Re	eports	System							
	₩ ₩ ◆ ₩₩	5	5			<u>88</u>	<u></u>								
Direct Receive	Receive by Serial	Locate and Move	Quick I Move	Direct Issue	Reconcile	Lease	Warranty Repairs	Find Ship or Consur							
	-			Activi	ties										
	E Receive Inventory (Short Form)														
Select View: Units Units Co															
				_	36	lect vie	w. Units,	Unit Cost							
9		<u>-</u> <u>Fi</u>	ilter Item	is By:	[???]			-							
Iter	m Id		Units	U. Co	ost Locat	tion	Lot/Seria	l No							
	S123	-	1	\$0.	00 DOC	К 🔻	1621734								
	A15	-	2	\$1.	50 DOC	К 🔻	1621735								
		-	0	\$0.	00	-									
								_							
F	Rev Date:	07/2	3/2008		Re	<u>c</u> eive		abels							